

MR16 6W DIM. TITANIUM LED SERIES



Model: 6MR16DIM/xxx/35W

Where xxx means 824-965 which indicates CRI and color temperature



ELECTRONIC TRANSFORMER COMPATIBILITY

Brand	Model	Compatibility
Hatch	RS12-15M-LED (DC1538K)	OK
	RS12-30M-LED (DC1418)	OK
	RS12-60M-LED (DC1340)	OK
	RS12-60M-LED (DC1323)	OK w/Noise
	RS12-60M (DC1124LED)	OK
	RS12-80M (DC1412)	X
	RS12-80M (DC5209)	OK
	RS12-80MGN (DC1440)	OK
	RS24-80M (DC-1128)	X
	RS12-80BFS (DC1528)	OK
	RS12-60BF-LED (DC1527K)	OK
	RL12-60A	OK
	RS12-80-277M (DC1522)	X
	RS12-80BF-277 (DC1528)	X
	RL12-75A-277	X
Ligtech	LET60	OK
	LET75	OK
	LET151R	OK
	LET75 277 R	OK
Wac	EN-1275-R-AR	OK

MAGNETIC TRANSFORMER COMPATIBILITY

Brand	Model	Compatibility
Elco	SSH-6626002	OK
Cooper	TF-149911-TP	OK
Juno	VF180-210	OK
Nora	TJ-H-277-80-1	OK
Halo	QE001292AS	OK
Hatch	DL1250B-H	OK

*GREEN CREATIVE has provided this transformer compatibility chart for guidance when selecting a transformer and lamp combination. Our lamps were tested for compatibility with the above listed transformers. Transformers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above transformers may affect performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.