



DIRECT PL

MODEL

Model: 5.5PLH/xxx/DIR/RC
 8.5PLH/xxx/DIR/R
 10.5PLH/xxx/DIR
 14.5PLH/xxx/DIR
 6PLV/xxx/DIR/R
 9.5PLV/xxx/DIR/R
 9.5PLV/xxx/DIR/RC
 11PLV/xxx/DIR/R
 17PLV/xxx/DIR

Where xxx means 824-965 which indicates CIR and color temperature



010321

ELECTRONIC BALLAST COMPATIBILITY

Model: 5.5PLHxxx/DIR/RC

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips-Advance	ICF-2S13-M1-BS-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S18-M1-BS-QS	PS	Compatible*	Compatible
Philips-Advance	ICF-2S18-H1-LD	PS	Compatible*	Compatible
Philips-Advance	I ZT-2S26-M5-BS	PS/DIM	Compatible	Compatible
Philips-Advance	I ZT-2S26-M5-LD	PS/DIM	Compatible	Compatible
Sylvania	QTP 1/2x13CF/UNV DM	PS	Compatible	Compatible
Sylvania	QTP 2x26CF/UNV DM	PS	Not Compatible	Compatible
Hatch	HC213PS/UV/D	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVBES	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C218UNVME	PS	Compatible	Compatible
Howard Lighting	EP2/13CF/MV/2	PS	Compatible	Compatible



DIRECT PL OMNI

ELECTRONIC BALLAST COMPATIBILITY

Model: 8.5PLH/xxx/DIR/R

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips-Advance	ICF-2S13-M1-BS-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S18-M1-BS-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S26-M1-BS-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S18-H1-LD	PS	Compatible	Compatible
Philips-Advance	ICF-2S26-H1-LD	PS	Compatible	Compatible
Philips-Advance	ICF-2S26-H1-LD-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S42-M2-LD	PS	Compatible	Compatible
Philips-Advance	IZT-2S26-M5-BS	PS/DIM	Compatible	Compatible
Philips-Advance	IZT-2S26-M5-LD	PS/DIM	Compatible	Compatible
Philips-Advance	IZT-2T42-M5-BS	PS/DIM	Not Compatible	Compatible
Philips-Advance	IZT-2T42-M5-LD	PS/DIM	Not Compatible	Compatible
Philips-Advance	VEZ-1T42-M2-BS	PS	Compatible**	Not Compatible
Sylvania	QTP 1/2x13CF/UNV DM	PS	Compatible	Compatible
Sylvania	QTP 1/2x18CF/UNV	PS	Compatible	Compatible
Sylvania	QTP 2x26CF/UNV CM	PS	Compatible	Compatible
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	Compatible**	Compatible
Hatch	HC213PS/UV/D	PS	Compatible	Compatible
Hatch	HC226PS/UV/D	PS	Compatible	Compatible
Hatch	HC242PS/UV/D	PS	Compatible	Not Compatible
Triad/Universal Lighting	C213UNVBES	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C218UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C218UNVBE	PS	Compatible	Not Compatible
Triad/Universal Lighting	C2642UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C2642UNVBE	PS	Compatible	Compatible
Howard Lighting	EP2/13CF/MV/2	PS	Compatible	Compatible
Howard Lighting	EP2/18CF/MV/2	PS	Compatible	Compatible
Howard Lighting	EP2/26CF/MV/2	PS	Compatible	Compatible
Howard Lighting	EP2/42CF/MV/2	PS	Compatible	Compatible
Sola	E-724-U-226-M1-S	PS	Compatible*	Compatible*
Fulham	WH2-277-L	IS	Compatible**	Compatible**
Fulham	WH3-277-L	IS	Compatible**	Compatible**
Fulham	WH4-277-L	IS	Compatible**	Compatible**
Fulham	RHA-UNV-213-C	PS	Not Compatible	Compatible
Fulham	RHA-UNV-226-C	PS	Not Compatible	Compatible
Fulham	RHA-UNV-242-C	PS	Not Compatible	Compatible



DIRECT PL OMNI

ELECTRONIC BALLAST COMPATIBILITY

Model: 10.5PLH/xxx/DIR

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips - Advance	ICF-2S13-M1-BS-QS	PS	Compatible	Compatible
Philips - Advance	ICF-2S18-M1-BS-QS	PS	Compatible	Compatible
Philips - Advance	ICF-2S26-M1-BS-QS	PS	Compatible	Compatible
Philips - Advance	ICF-2S18-H1-LD	PS	Compatible	Compatible
Philips - Advance	ICF-2S26-H1-LD	PS	Compatible	Compatible
Philips - Advance	ICF-2S26-H1-LD-QS	PS	Compatible	Compatible
Philips - Advance	ICF-2S42-M2-LD	PS	Compatible	Compatible
Philips - Advance	IZT-2S26-M5-BS	PS/DIM	Compatible	Compatible
Philips - Advance	IZT-2S42-M5-BS	PS/DIM	Compatible	Compatible
Philips - Advance	VEZ-1T42-M2-BS	PS	Compatible	Compatible
Sylvania	QTP 1/2x13CF/UNV DM	PS	Compatible	Compatible
Sylvania	QTP 2x26CF/UNV DM	PS	Compatible	Compatible
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	Not Compatible	Compatible
Hatch	HC213PS/UV/D	PS	Compatible	Compatible
Hatch	HC226PS/UV/D	PS	Compatible	Compatible
Hatch	HC242PS/UV/D	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVBES	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C218UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C2642UNVME	PS	Compatible	Compatible
Howard Lighting	EP2/13CF/MV/2	PS	Compatible	Compatible
Howard Lighting	EP2/18CF/MV/2	PS	Compatible	Compatible
Howard Lighting	EP2/26CF/MV/2	PS	Compatible	Compatible
Howard Lighting	EP2/42CF/MV/2	PS	Compatible	Compatible
Sola	E-724-U-226-M1-S	PS	Compatible	Compatible
Fulham	WH2-277-L	PS	Compatible	Compatible
Fulham	WH3-277-L	PS	Compatible	Compatible
Fulham	WH4-277-L	PS	Compatible	Compatible
Fulham	RHA-UNV-213-C	PS	Not Compatible	Compatible
Fulham	RHA-UNV-226-C	PS	Not Compatible	Compatible
Fulham	RHA-UNV-242-C	PS	Compatible	Compatible



DIRECT PL OMNI

ELECTRONIC BALLAST COMPATIBILITY

Model: 14.5PLH/xxx/DIR

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Universal - Triad	C242UNVME	PS	Compatible	Compatible
Universal - Triad	C2642UNVBE	PS	Compatible	Compatible
GE	GEC242-MVPS-3W	PS	Compatible	Compatible
GE	GEC242-MVPS-SE	PS	Compatible	Compatible
Hatch	HC242PS/UV/D	PS	Compatible	Compatible
Philips - Advance	ICF-2S42-M2-LD	PS	Compatible	Compatible
Philips - Advance	REZ-1T42-M2-LD	PS	Compatible*	Compatible
Philips - Advance	VEZ-1T42-M2-BS	PS	Compatible**	Compatible
Philips - Advance	IZT-2S26-M5-BS	PS	Compatible	Compatible
Philips - Advance	IZT-2S26-M5-LD	PS	Compatible	Compatible
Philips - Advance	IZT-2T42-M5-BS	PS	Compatible	Compatible
Philips - Advance	IZT-2T42-M5-LD	PS	Compatible	Compatible
Fulham	RHA-UNV-242-C	PS	Compatible	Compatible
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	Not Compatible	Compatible
Sylvania	2X26CF/UNV DIM DM	PS	Not Compatible	Compatible

ELECTRONIC BALLAST COMPATIBILITY

Model: 6PLV/xxx/DIR/R

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips-Advance	ICF-2S13-M1-BS-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S18-M1-BS-QS	PS	Compatible*	Compatible
Philips-Advance	ICF-2S18-H1-LD	PS	Compatible	Compatible
Philips-Advance	IZT-2S26-M5-BS	PS/DIM	Not Compatible	Not Compatible
Philips-Advance	IZT-2S26-M5-LD	PS/DIM	Not Compatible	Not Compatible
Sylvania	QTP 1/2x13CF/UNV DM	PS	Compatible	Compatible
Sylvania	QTP 2x26CF/UNV DM	PS	Not Compatible	Compatible
Hatch	HC213PS/UV/D	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVBES	PS	Compatible	Compatible
Triad/Universal Lighting	C213UNVME	PS	Compatible	Compatible
Triad/Universal Lighting	C218UNVME	PS	Compatible	Compatible
Howard Lighting	EP2/13CF/MV/2	PS	Not Compatible	Not Compatible



DIRECT PL OMNI

ELECTRONIC BALLAST COMPATIBILITY

Model: 9.5PLV/xxx/DIR/R 9.5PLV/xxx/DIR/RC

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips-Advance	ICF-2S13-M1-BS-QS	PS	Compatible	Not Compatible
Philips-Advance	ICF-2S18-M1-BS-QS	PS	Compatible	Not Compatible
Philips-Advance	ICF-2S26-M1-BS-QS	PS	Compatible	Not Compatible
Philips-Advance	ICF-2S18-H1-LD	PS	Compatible	Compatible
Philips-Advance	ICF-2S26-H1-LD	PS	Compatible	Not Compatible
Philips-Advance	ICF-2S26-H1-LD-QS	PS	Compatible	Compatible
Philips-Advance	ICF-2S42-M2-LD	PS	Compatible	Compatible
Philips-Advance	IZT-2S26-M5-BS	PS/DIM	Compatible	Compatible
Philips-Advance	IZT-2S26-M5-LD	PS/DIM	Compatible	Compatible
Philips-Advance	IZT-2T42-M5-BS	PS/DIM	Not Compatible	Compatible
Philips-Advance	IZT-2T42-M5-LD	PS/DIM	Not Compatible	Compatible
Philips-Advance	VEZ-1T42-M2-BS	PS	Compatible**	Not Compatible
Sylvania	QTP 1/2x18CF/UNV	PS	Compatible	Not Compatible
Sylvania	QTP 2x26CF/UNV DM	PS	Compatible	Not Compatible
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	Compatible	Not Compatible
Hatch	HC213PS/UV/D	PS	Compatible	Not Compatible
Hatch	HC226PS/UV/D	PS	Compatible	Not Compatible
Hatch	HC242PS/UV/D	PS	Compatible	Not Compatible
Triad/Universal Lighting	C213UNVBES	PS	Compatible*	Not Compatible
Triad/Universal Lighting	C218UNVME	PS	Compatible	Not Compatible
Triad/Universal Lighting	C218UNVBE	PS	Compatible	Not Compatible
Triad/Universal Lighting	C2642UNVME	PS	Compatible	Not Compatible
Triad/Universal Lighting	C2642UNVBE	PS	Compatible	Not Compatible



DIRECT PL OMNI

ELECTRONIC BALLAST COMPATIBILITY

Model: 11PLV/xxx/DIR/R

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips - Advance	ICF-2S13-M1-BS-QS	PS	Compatible	Not Compatible
Philips - Advance	ICF-2S18-M1-BS-QS	PS	Compatible	Not Compatible
Philips - Advance	ICF-2S26-M1-BS-QS	PS	Compatible	Not Compatible
Philips - Advance	ICF-2S18-H1-LD	PS	Compatible	Compatible
Philips - Advance	ICF-2S26-H1-LD	PS	Compatible	Not Compatible
Philips - Advance	ICF-2S26-H1-LD-QS	PS	Compatible	Compatible
Philips - Advance	ICF-2S42-M2-LD	PS	Compatible	Not Compatible
Philips - Advance	IZT-2S26-M5-BS	PS/DIM	Compatible	Compatible
Philips - Advance	IZT-2S26-M5-LD	PS/DIM	Compatible	Compatible
Philips - Advance	IZT-2T42-M5-BS	PS/DIM	Not Compatible	Compatible
Philips - Advance	IZT-2T42-M5-LD	PS/DIM	Not Compatible	Compatible
Philips - Advance	VEZ-1T42-M2-BS	PS	Compatible**	Not Compatible
Sylvania	QTP 1/2x13CF/UNV DM	PS	Compatible	Not Compatible
Sylvania	QTP 2x26CF/UNV DM	PS	Compatible	Not Compatible
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	Compatible**	Not Compatible
Hatch	HC213PS/UV/D	PS	Compatible	Not Compatible
Hatch	HC226PS/UV/D	PS	Compatible	Not Compatible
Hatch	HC242PS/UV/D	PS	Compatible	Not Compatible
Triad/Universal Lighting	C213UNVBES	PS	Compatible*	Not Compatible
Triad/Universal Lighting	C213UNVME	PS	Compatible	Not Compatible
Triad/Universal Lighting	C218UNVME	PS	Compatible	Not Compatible
Triad/Universal Lighting	C2642UNVME	PS	Compatible	Not Compatible
Triad/Universal Lighting	C2642UNVBE	PS	Compatible	Not Compatible
Howard Lighting	EP2/13CF/MV/2	PS	Compatible	Not Compatible
Howard Lighting	EP2/18CF/MV/2	PS	Compatible	Not Compatible
Howard Lighting	EP2/26CF/MV/2	PS	Compatible	Not Compatible
Howard Lighting	EP2/42CF/MV/2	PS	Compatible	Not Compatible
Sola	E-724-U-226-M1-S	PS	Compatible	Not Compatible

DIRECT PL OMNI

ELECTRONIC BALLAST COMPATIBILITY

Model: 17PLV/xxx/DIR/R

Brand	Model	Type	Compatibility
			(Ballasts are compatible with 120V & 277V unless otherwise noted)
			1 lamp
Universal - Triad	C242UNVME	PS	Compatible*
Universal - Triad	C2642UNVBE	PS	Compatible
GE	GEC242-MVPS-3W	PS	Compatible
GE	GEC242-MVPS-SE	PS	Compatible
Hatch	HC242PS/UV/D	PS	Compatible
Philips - Advance	ICF-2S42-M2-LD	PS	Compatible
Philips - Advance	REZ-1T42-M2-LD	PS	Compatible*
Philips - Advance	VEZ-1T42-M2-BS	PS	Compatible**
Fulham	RHA-UNV-242-C	PS	Compatible
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	Not Compatible

* Only 120V

** Only 277V

GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps. Lamps that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.