


CCT SELECT PINFIT PL OMNI

MODEL

6.8PLO/8CCTS/HYB/PF
9PLO/8CCTS/HYB/PF/R



BALLAST COMPATIBILITY

Model: 6.8PLO/8CCTS/HYB/PF

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips-Advance	ICF-2S13-M1-BS-QS	PS	Compatible	
	ICF-2S18-M1-BS-QS	PS	Compatible	
	ICF-2S18-H1-LD	PS	Compatible	
Howard Lighting	EP2/13CF/MV/2	PS	Compatible	
Keystone	KTEB-213-UV-RS-DW	RS	Compatible	
Sylvania	QTP 1/2X13CF/UNV DM	PS	Compatible	
	QTP 2X26CF/UNV DM	PS	Compatible	
Triad/Universal Lighting	C213UNVBES	PS	Compatible	
	C213UNVME	PS	Compatible	
	C218UNVME	PS	Compatible	
Philips-Advance	LC-13-TP	PS	Compatible**	N.A.
	LO-13-22	PS	Compatible**	N.A.
	VLO-13-TP	PS	Compatible*	N.A.
Keystone	CC1322MTP	PS	Compatible**	N.A.
Robertson	SIP(3P10083)	IS	Compatible**	N.A.
Sola	FCF-13-TP	PS	Compatible**	N.A.

BALLAST COMPATIBILITY

9PLO/8CCTS/HYB/PF/R

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 lamp	2 lamps
Philips-Advance	ICF-2S26-M1-BS-QS	PS	Compatible	
	ICF-2S26-H1-LD	PS	Compatible	
	ICF-2S13-M1-BS-QS	PS	Compatible	
	ICF-2S26-M1-BS-QS	PS	Compatible	
	ICF-2S18-H1-LD	PS	Compatible	
	ICF-2S42-M2-LD	PS	Compatible	
	IZT-2S26-M5-BS	PS/DIM	Not Compatible	
	IZT-2S26-M5-LD	PS/DIM	Compatible	
	IZT-2T42-M5-LD	PS/DIM	Compatible	Not Compatible
	VEZ-1T42-M2-BS	PS	Compatible*	N.A.
	IZT-2T42-M5-BS	PS/DIM	Not Compatible	

CCT SELECT PINFIT PL OMNI

Sylvania	QTP 2X26/32/42CF/UNV DM	PS	Compatible*	Not Compatible
	QTP 1/2X13CF/UNV DM	PS	Compatible	
	QTP 2X26CF/UNV DM	PS	Compatible	
Hatch	HC226PS/UV/D	PS	Compatible*	Compatible
	HC242PS/UV/D	PS	Compatible*	Compatible
	HC213PS/UV/D	PS	Compatible*	Compatible
Triad/Universal Lighting	C2642UNVBE	PS	Compatible	
	C2642UNVME	PS	Compatible	
	C213UNVBES	PS	Compatible	
	C213UNVME	PS	Compatible	
	C218UNVBE	PS	Not Compatible	
	C218UNVME	PS	Compatible	
Howard Lighting	EP2/26CF/MV/2	PS	Compatible*	Compatible
	EP2/13CF/MV/2	PS	Compatible	
	EP2/18CF/MV/2	PS	Compatible*	Compatible
	EP2/42CF/MV/2	PS	Not Compatible	Compatible
Sola	E-724-U-226-M1-S	PS	Compatible	Compatible**
Fulham	RHA-UNV-226-C	PS	Not Compatible	
	RHA-UNV-213-C	PS	Not Compatible	
	RHA-UNV-242-C	PS	Not Compatible	
	WH2-277-L	IS	Compatible*	
	WH3-277-L	IS	Compatible*	
	WH4-277-L	IS	Compatible*	
Philips-Advance	H-1Q26-TP-BLS	PS	Compatible**	N.A.
Robertson	HP28P	PS	Compatible**	N.A.
	HP22627P	PS	N.A.	Compatible*
	HP2627P	PS	Compatible*	N.A.
	O1527P(3P10104)	PS	Compatible*	

* Only 277V compatible

** Only 120V compatible

GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.