



DIRECT PLL 13W

MODEL

Model: 13PLL/xxx/GL/DIR

Where xxx means 824-965 which indicates CIR and color temperature



ELECTRONIC BALLAST COMPATIBILITY

Series	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 Lamp	2 Lamps
Philips-Advance	ICN-1TTP40-SC	IS	OK	X
Philips-Advance	ICN-2TTP40-SC	IS	OK	OK
Philips-Advance	ICF-2S42-M2-LD	PS	Only 120V OK	OK
Sylvania	QHE 1x40DL/UNV ISN-SC	IS	OK	X
Sylvania	QTP 2X26/32/42CF/UNV DM	PS	X	OK
Universal-Triad	C242UNVME	PS	OK	OK
Sylvania	QHE 2X40DL/UNV ISN-SC	IS	OK	OK
GE - UltraMax	GEC140MAX-A	IS	OK	X
GE - UltraMax	GEC240MAX-A	IS	Only 120V OK	OK

OK - Fully Compatible

X - Not compatible

GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps. sts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.