

T8 DIR FAMILY

MODEL

Model: 8T8/2F/xxx/DIR/RD

10T8/3F/xxx/DIR 11T8/4F/xxx/DIR 11T8/4F/xxx/DIR/C 14T8/4F/xxx/DIR 15T8U6/xxx/DIR

* 1) =) \$

Where xxx means 824-965 which indicates CRI and color temperature

0 - 10V DIMMER COMPATIBILITY

Model: 8T8/2F/xxx/DIR/RD 11T8/4F/xxx/DIR 10T8/3F/xxx/DIR 11T8/4F/xxx/DIR/C 14T8/4F/xxx/DIR

| Brand | Series | Model | Load (w) | Ballast | |
|----------|------------|-----------|-------------|------------------|------------------------|
| | | | | General Electric | Keystone |
| | | | | GE132MVPSN-V03 | KTLD-2T8LED-UV-IS-VDIM |
| LUXdrive | N.A. | 0A019 | N.A. | Compatible | Compatible |
| Lutron | Nova | NTSTV-DV | 960W | - | Compatible |
| | Nova | NFTV | N.A. | - | Compatible |
| | Diva | DVSTV | 960W | - | Compatible |
| | Diva | DVSCTV | 1000W | - | Compatible |
| Leviton | Illumatech | IP710-LFZ | 1200W | - | Compatible |

0 - 10V DIMMER COMPATIBILITY

Model: 15T8/U6/xxx/DIR

| 11100011 1010/00/2007 2111 | | | | | | | | |
|----------------------------|------------|-----------|-------------|-------------|------------------------|--|--|--|
| Brand | Series | Model | Load (w) | Ballast | | | | |
| | | | | Philips | Keystone | | | |
| | | | | IZT-2S32-SC | KTLD-2T8LED-UV-IS-VDIM | | | |
| LUXdrive | N.A. | 0A019 | N.A. | Compatible | Compatible* | | | |
| Lutron | Nova | NTSTV-DV | 960W | - | Compatible* | | | |
| | Nova | NFTV | N.A. | - | Compatible* | | | |
| | Diva | DVSTV | 960W | - | Compatible* | | | |
| | Diva | DVSCTV | 1000W | - | Compatible* | | | |
| Leviton | Illumatech | IP710-LFZ | 1200W | - | Compatible* | | | |

^{*}Only 1 lamp compatible.

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.