



**Titanium Series MR16 6W  
6MR16DIM**



## Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)										
				HALO CAN		ELCO		Juno	NORA		ESBCO		ELG	
				1	2	1	2	1	1	2	1	2	1	2
LUTRON	Abella	ABLV-1000M	1000	X		15-100%*		X		X				OK**
	Maestro	MALV-600	600	X		X		X		OK**		X		X
	Skylark	SLV-600P	600	X		OK		OK		15-100%**		X		15-100%**
Legrand	Harmony	H703PTU	600	X		15-100%		15-100%		OK**		X		OK**
	Adorne	ADTP703TU	700	X		OK		OK		OK		X		OK**
LEVITON	Sure Slide	6613-PL	600	X		OK		OK		OK		X		X
	VIZA+	VPM10-1LX	1000	X		OK		X		OK**		X		OK**
COOPER	Devine	DAL06P	300	X		X		OK		15-100%**		X		OK**
	Aspire	9536	600	X		X		X		X		X		X

\*Minimum 2 lamps

\*\*Minimum 3 lamps

**Table Key**  
 OK= Fully compatible  
 \_\_-\_\_% = Compatible within this range  
 X= Incompatible

\*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a



**Titanium Series MR16 6W  
6MR16DIM**



**Electronic Dimmer Switch Compatibility**

Brand	Series	Model	Load	Dimmability (# of lamps)																														
				Hatch																														
				RS12-60M-LED (DC1340)						RS12-60M (DC1124LED)						RS12-60M (DC1130)						RS12-80M (DC1412)						RS12-30M (DC1413)					RS12-15M-LED (DC1513K)	
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	1	2
LUTRON	Rotary	6B38	600	X																														
	Nova	NTELV-300	300	OK						OK*						OK						X						OK					OK	
LEVITON	Decora	6615P	1000	X						X						40-100% *						40-100% **						X					X	

\*Maximum 2 lamps

\*\*Minimum 2 lamps

**Table Key**

OK= Fully compatible

\_\_-\_\_% = Compatible within this range

X= Incompatible

\*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.