



# PAR56 40W DIM.

## MODEL

Model: 40PAR56DIM/xxxxyyy

Where xxx means 824-965 which indicates CRI and color temperature

Where yyy means beam angle



## ELV DIMMER COMPATIBILITY

| Brand   | Series          | Model      | Load (W) | Dimming Range | Dimmability |
|---------|-----------------|------------|----------|---------------|-------------|
| Lutron  | Maestro         | MAELV-600  | 600      | 0-100%        | Compatible  |
|         | Nova            | NTELV-600  | 600      | 0-100%        | Compatible  |
|         | Skylark Contour | CTELV-303P | 300      | 0-100%        | Compatible  |
|         | Diva            | DVELV-300P | 300      | 0-100%        | Compatible  |
|         | Caseta          | PD-5NE     | 250      | 0-100%        | Compatible  |
| Leviton | Illumatech      | IPE04-1LZ  | 300      | 10-100%       | Compatible  |

## 120V DIMMER COMPATIBILITY

| Brand   | Series           | Model     | Load (W) | Dimming Range | Dimmability    |
|---------|------------------|-----------|----------|---------------|----------------|
| Lutron  | Diva             | DV-600P   | 600      | -             | Not Compatible |
|         | Toggler          | TG-600P   | 600      | -             | Not Compatible |
|         | Skylark Contour  | CTCL-153P | 150      | 0-100%        | Compatible     |
|         | Diva             | DVCL-153P | 150      | 0-100%        | Compatible     |
|         | Maestro C•L      | MACL-153M | 150      | 0-100%        | Compatible     |
| Leviton | Sureslide Decora | 6674      | 600      | 0-100%        | Compatible     |
|         | Trimatron        | 6602      | 600      | -             | Not Compatible |
| Cooper  | Aspire           | 9536      | 1,000    | 0-100%        | Compatible     |

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.