


## T8 HYB (UL Type A + B - Direct or Single and Double Ended Bypass)

### MODEL

12T8/4F/8CCTS/HYB/C  
15T8/4F/8CCTS/HYB/C



### EMERGENCY BALLAST COMPATIBILITY

Model: 12T8/4F/8CCTS/HYB/C 15T8/4F/8CCTS/HYB/C		
Brand	Model	Compatibility
Fulham	FH7-UNV-500L-CEC	Compatible
	FH11-UNV-750L-CEC	Compatible
	FH12-UNV-1400L-CEC	Compatible
	FH4-DUAL-700L	Not Compatible
	FH3-DUAL-450L	Not Compatible
	FH5-DUAL-1400L	Compatible
	FH12-UNV-1400L	Not Compatible
Bodline	B50	Not Compatible
	B30 ST	Not Compatible
	B54	Not Compatible
	B60	Not Compatible
	B100	Not Compatible
	LP550	Compatible
	LP600	Not Compatible
IOTA	ICE-80	Not Compatible
	I-232	Not Compatible
	I-162	Compatible
	I-32	Not Compatible
	ISL-54	Not Compatible
	ISL-540	Not Compatible
	ISD-80	Not Compatible
Lithonia	EI500	Not Compatible
	PSQ500QD	Not Compatible
	PS1400QD	Not Compatible
ALP	EFP 32GS	Not Compatible
KEYSTONE	KT-EMRG-1400	Not Compatible
	KT-EMRG-500-SL	Not Compatible

GREEN CREATIVE has provided this emergency ballast compatibility chart for guidance when selecting an emergency ballast and lamp combination. Lamps were tested for compatibility with the above listed emergency ballasts. Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above emergency ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.